



E10

## SPECIFICATIONS

### AM/FM/Shortwave Radio

The sleek, sophisticated lines of the E10 make this a radio you'll be proud to display. It was also designed for your listening pleasure. With 550 programmable presets, you can set the built-in alarm clock to wake you up to just about anything you want to hear. Plug it in or run it off of Ni-MH batteries that recharge internally. Either way, you'll get great reception, no matter where you are.



## FEATURES

- FM frequency range: 87 - 108 MHz (for North America); 76 - 108 MHz (for Japan)
- Shortwave frequency range: 1711 - 29999KHz
- 9/10KHz step selector for Medium Wave (AM) reception
- 1/5KHz step for the display of Shortwave
- SW IF SET feature, shifts the intermediate frequency to minimize interference during Shortwave reception
- Shortwave antenna trimmer
- ATS (Auto Tuning System) for the automatic memory storage of FM/MW stations
- Manual tuning
- Auto scan tuning
- Direct keypad frequency entry
- Digital tuning knob with lock feature
- 550 programmable memories
- Memory page customization
- Auto-scan and manually scan stations stored into memory
- Direct memory access
- Fast/slow tuning rate selection for manual tuning
- Digital clock
- Sleep timer
- Two turn-on timers with station memory
- 12/24 hour format selection
- Snooze function: 10 minutes, repeated three times
- FM stereo/mono selection
- High/low tone control
- LCD backlight with user control
- Key lock
- Built-in Ni-MH battery charger
- System set codes
- Power source: 4 AA batteries or AC adapter (included)
- Dimensions: 7-1/2" x 4-1/2" x 1-1/2" and 188 x 117 x 38 mm (W x H x D)
- Weight: 1 lb. 1oz. and 482 g
- Accessories: Owner's manual, AC adapter, protective pouch

Available in: *Gunmetal*