

# FR1000 VOICELINK

## SPECIFICATIONS

### Self-Powered Hand-Crank AM/FM/NOAA Weather/2-Way GMRS Clock Radio with Flashlight, Siren and Cell Phone Charger

Stay connected with the Voicelink FR-1000. This emergency crank radio combines two-way radio with GMRS technology, built-in flashlight, cell-phone charger and access to weather channels to prepare you for any emergency situation. Get prepared and get connected with the Voicelink FR-1000



Flashing Beacon



Cell Phone Charger



Flashlight



Headphone Jack



Crank Power



Emergency Siren



Receives FM Band



Receives AM Band



Receives Weather Band



General Mobile Radio System



## FEATURES

- 22 GMRS (General Mobile Radio System)/FRS (Family Radio System) channels
- 121 privacy codes (38 CTCSS / 83 DCS)
- AM/FM receiver
- VOX (Voice operated transmission)
- Selectable call alert
- NOAA weather radio
- NOAA weather alert
- Scan function
- Monitor function
- Dual watch function
- Roger beep tone
- Silent operation
- Keypad lock
- Power HI/LO settings
- Watch/Alarm clock function
- SOS function (beacon light)
- Siren
- Flashlight
- Crank dynamo battery charging capability
- Battery meter/battery low indicator
- GMRS/FRS: UHF 462.5500 ~ 467.7125 MHz
- NOAA weather radio: 162.550 ~ 162.525MHz
- FM frequencies: 87.5 ~ 108.0MHz
- AM frequencies: 520 ~ 1710kHz
- LCD display
- 12hr (AM/PM) clock function
- Alarm clock function
- SNOOZE function
- External speaker/microphone jack
- Cell phone charging jack
- AC/DC adapter charging jack
- Power source: 4 AA alkaline batteries or NiMH battery pack (5 pcs AAA Ni-MH batteries, 7mAh 6.0V)
- Dimensions: 11.09" x 6.16" x 4.13" and 281.7mm x 156.5mm x 105.0mm (W x H x D)\*\*\*including handles/knobs
- Weight: 2.17 lbs. and .985 kg
- Accessories: owner's manual, rechargeable battery, AC adaptor

