

G4000A

High-Performance Portable



Specifications

Grundig G4000A AM/FM/Shortwave Radio

The G4000A is an enthusiast-quality world receiver, packed with the power to scan and lock-on to even the weakest Shortwave signals with rock-solid precision. The G4000A is capable of receiving AM, FM, continuous Shortwave, and even SSB (Single Sideband) for two-way Shortwave communications such as amateur radio operators.

Features

- FM-Stereo; AM; Full-Shortwave (1711-29999 KHz)
- Dual Conversion AM/SW Circuitry With SSB
- PLL Digital Tuner With LCD Digital Display
- Display Light
- 40 Random Programmable Memory Presets
- Memory-Free Feature Locates Unused Memories
- Memory Scan And Direct Memory Access
- Tuning Via Up/Down Buttons, Auto-Scan And Direct Frequency Entry
- Dual 24 Hour Clocks With Alarm (tone & radio), Snooze And Sleep Timer
- High/Low Tone Control
- Wide/Narrow Bandwidth Filter
- Stereo Earphone Socket
- Stereo/Mono Switch
- DX/Local Switch
- All Antennas Built-In And Socket For External Shortwave Antenna
- Included: Owner's Manual, One-Year Warranty, AC Adapter/Charger, Supplementary Wire Antenna, Wrap-Around Carrying Case
- Power Source: 6 AA Batteries (not included); AC Adapter (included)
- Dimensions: 7-3/4"W x 4-1/2"H x 1-1/4"D (198 x 117 x 33 mm)
- Weight: 1 lb. 5 oz. (596 g)