

# S350

## High-Performance Field Radio



## Specifications

### Grundig S350 AM/FM/Shortwave Field Radio

The S350 blends the best of yesterday and today. With the look of a retro field radio sporting a rugged body and military-style controls—the S350 also features today's innovation for excellent AM, FM, and Shortwave reception and a large, full-range speaker for clear sound.

The external antenna input is ideal for enthusiasts. And features such as line-level output, separate bass, treble, and RF gain control, wide and narrow bandwidth filter controls, put you in the command seat for tuning in to local and international news, music, and sports.

## Features

- AM 530-1710 KHz
- FM 88-108 MHz
- Shortwave - continuous coverage from 3 to 28 MHz. This includes 13 international broadcast bands. 11, 13, 15, 16, 19, 22, 25, 31, 41, 49, 60, 75 and 90 meters
- Highly sensitive and selective analog tuner circuitry
- Digital frequency readout
- Liquid Crystal Display, LCD, for frequency and clock
- Digital clock with selectable 12/24 hour format
- Wake-up timer (use as radio-play alarm clock)
- Power failure backup feature
- Sleep timer
- Main Tuning knob and independent fine-tuning control knob
- Variable RF Gain Control
- Rotary volume control
- Variable, independent bass and treble control
- Low-pass filter for shortwave and AM reception
- Left/Right line level outputs (stereo in FM)
- Stereo/mono switch
- Earphone socket
- Strap type carrying handle
- Built in telescopic antenna for FM and shortwave
- Built in ferrite bar antenna for AM
- Jacks for supplementary AM, FM and shortwave antennas
- Power Source: 4 D Batteries (not included) or AC Adapter (included)
- Dimensions: 10-3/4"W x 7"H x 3-1/2"D (272 x 175 x 89 mm)
- Weight: 3 lb. 2 oz. (1.42 Kg)

