

Sound100

SPECIFICATIONS

AM/FM Radio

Etón has updated the retro glamour of radios past with swooping, curved lines and today's in-demand colors. This little radio packs a wallop, making it ideal for home or office use. Go ahead...pick your favorite color.



Also available in:



WHITE



SILVER



BLUE



RED

FEATURES

- AM frequency coverage: 530 -1710 KHz / step 10 KHz
- FM frequency coverage: 87.50 - 108.00 MHz / 0.10 MHz
- Memory preset station assignments: 5 AM and 5 FM for total of 10 presets
- Encoder volume control
- Manual scan tuning
- Auto station: locates and locks in on the strongest station
- Auto tune provides a programmed service list
- AM/FM tuner type and circuitry: a high-sensitivity digital Phased-Locked Loop Tuner (PLL) locks in the frequency and provides excellent AM/FM reception and selectivity
- LCD type: 97 Segment, 80.8mm(L) x 36.8mm(W) x Max8.6mm(H)
- Viewing area: 62.0mm(W) x 26.0mm(H), gentle illumination (will not keep you awake), blue backlight, black characters, segment display (displays time, station, alarm, sleep, band and presets)
- Clock functions: 12 hours format selectable, alarm (wake up to radio or buzzer), sleep timer (programmable minimum range 15 minutes and maximum range 90 minutes), snooze (mode duration: 5 minutes)
- Auxiliary inputs:
 - 3.5mm Aux line-in for MP3/CD connection
 - 3.5mm audio line-out
 - Input for AC adapter (included), input for earphones (not included)
 - Amplifier: single channel, earphone, AB
- Speaker type: The 3" full range, magnetically shielded, high-fidelity, front firing, mono speaker driver with magnet is capable of producing a wide range of frequencies and produces incredibly powerful, distortion-free, room filling sound
- RMS power output : 3Wrms at 10% THD, 2 Wrms at 1% THD
- Frequency response range: 80Hz- 20KHz
- Base port
- Audio output: 5 Watt
- Unit power: 15 Watt
- FM antenna type: Chrome plated aerial, 360 degree, swivel-rotary type, telescopic.
- AM antenna type: built-in loop
- Protection: rubber feet prevent scratching and movement
- Input Voltage: 120V AC 60 Hz power supply, IN: 230VAC 50HZ; OUT: AC 12V/1A, UL approval
- Battery back-up: stores real time during a power failure (will not hold station presets and alarm settings during power failure), requires 2 AA batteries (not included)
- Power source: AC adaptor (included)
- Dimensions: 8.27" x 4.53" x 5.1" and 21,0 x 11,5 x 13,0 cm (W x H x D)
- Weight: 3.96 lbs. with adapter / 1.8 kg with adapter
- Accessories: Owner's manual, AC adapter, infrared remote control