

# SOLARLINK FR600

Self-Powered Digital AM/FM/SW/NOAA, S.A.M.E. Weather Radio with Flashlight, Siren, Solar Power and Cell Phone Charger



## Features:

- Digital tuner with AM (520-1700 KHz), FM (88-108 MHz), Shortwave (5800-12200 KHz)
- NOAA weather with alert – all 7 channels plus “Alert”
- S.A.M.E. Technology (location based weather alerts)
- Digital tuner with AM, FM, WB, SW bands
- Digital display – easy to read, large, green LED illuminated backlit
- Digital clock function: 12-hour clock with alarm function, snooze, and sleep timer
- Can be powered from four different sources:
  - 1) Dynamo/hand crank which charges the Ni-MH battery
  - 2) From 3 AA batteries (not included)
  - 3) From the AC via USB adapter (not included)
  - 4) Solar power which charges Ni-MH battery
- Built-in four white LED, one red LED lights with magnifying lens for brighter, more powerful light source
- Emergency siren/flashing beacon
- USB cell phone charger (USB cable not included)
- Rotary all band selector knob
- Connectors, with rubber gaskets/plugs to seal out moisture, 3.5 mm headphone output, DC-in, USB phone charger and AUX-IN input
- Telescopic antenna provided for maximum range and reception
- Power source: built-in rechargeable Ni-MH battery pack; 3 AA batteries (not included); AC adapter (not included); solar power
- Dimensions: 7.75" X 8.5" X 2.5" and 196.9 x 215.9 x 63.5 mm (W x H x D)
- Weight: 1.9 lbs. and 0.86 kg
- Accessories: owner's manual, warranty card

\* Specifications subject to change.

 Receives AM/FM Band	 Specific Area Message Encoding	 Nat. Oceanic & Atmospheric Admin	 Receives Weather Band	 Receives Shortwave Band
 Digital Tuning	 Crank Power	 USB Cell Phone Charger	 Solar Powered	 LED Flashlight
 Flashing Beacon	 Emergency Siren	 Alarm Clock	 USB Compatible	
 Line In (AUX)	 Splash Resistant	 Headphone Jack		

**etón**  
CORPORATION